















**ESD** 

TVS

MOS

LDO

Diode

Sensor

DC-DC

# **Product Specification**

Domestic Part Number	EV2SC3357-SB
Overseas Part Number	2SC3357
▶ Equivalent Part Number	2SC3357

"SB" means SOT-89






#### ■ NPN Transistors

#### ■ Features

- Low noise and high gain
- High power gain
- Large Ptot



■ Simplified outline(SOT-89)

#### ■ Absolute Maximum Ratings Ta = 25°C

Parameter	Symbol	Rating	Unit	
Collector - Base Voltage	Vсво	20		
Collector - Emitter Voltage	VCEO	V		
Emitter - Base Voltage	VEBO	3		
Collector Current - Continuous	Ic	100	mA	
Collector Power Dissipation	Pc	1.2	W	
Junction to Ambient Resistance	Rth (j-a)	62.5	°C/W	
Junction Temperature	TJ	150	•0	
Storage Temperature Range	Tstg	-55 to 150	$^{\circ}$	

#### ■ Electrical Characteristics Ta = 25°C

Parameter	Symbol	Test Conditions	Min	Тур	Max	Unit
Collector- base breakdown voltage	Vсво	Ic= 100 μA, IE= 0	20			
Collector- emitter breakdown voltage		Ic= 1 mA, I <sub>B</sub> = 0	12			V
Emitter - base breakdown voltage	VEBO	IE= 100 μ A, IC= 0	3			
Collector-base cut-off current	Ісво	Vcb= 20V , IE= 0			1	
Emitter cut-off current	ІЕВО	V <sub>EB</sub> = 3V , I <sub>C</sub> =0			1	uA
Collector-emitter saturation voltage	VCE(sat)	Ic=50 mA, Iв=5mA			0.4	V
Base - emitter saturation voltage	VBE(sat)	Ic=50 mA, Iв=5mA			1.2	v
DC current gain (Note.1)	hfe	VcE= 10V, Ic= 20mA	50		250	
Insertion Power Gain	S21e  <sup>2</sup>	VcE = 10V, Ic = 20mA, f= 1GHz		9		
Noise Figure	NF	VcE = 10V, Ic = 7mA, f= 1GHz		1.1		dB
Noise i igure		VcE = 10V, Ic = 40mA, f= 1GHz		1.8	3	
Reverse Transfer Capacitance		Vcb= 10V, IE= 0,f=1MHz			1	pF
Transition frequency	f⊤	VcE= 10V, Ic= 20mA		6.5		GHz

Note.1: Pulse measurement: PW  $\leqslant$  350 us, Duty Cycle  $\leqslant$  2%


#### ■ Classification of hfe

Туре	2SC3357-F	2SC3357-E			
Range	80-160	125-250			
Marking	RF	RE			




#### ■ Typical Characterisitics


#### TOTAL POWER DISSIPATION vs. AMBIENT TEMPERATURE




DC CURRENT GAIN vs. **COLLECTOR CURRENT** 




INSERTION POWER GAIN, MAG vs. FREQUENCY




REVERSE TRANSFER CAPACITANCE vs. COLLECTOR TO BASE VOLTAGE



**GAIN BANDWIDTH PRODUCT** vs. COLLECTOR CURRENT




**INSERTION POWER GAIN** 






#### ■ Typical Characterisitics


## NOISE FIGURE vs. COLLECTOR CURRENT









#### ■ SOT-89









#### **DIMENSIONS** (mm are the original dimensions)

UNIT	Α	b <sub>p1</sub>	b <sub>p2</sub>	b <sub>p3</sub>	С	D	E	е	e <sub>1</sub>	HE	Lp	w
mm	1.6 1.4	0.48 0.35	0.53 0.40	1.8 1.4	0.44 0.23	4.6 4.4	2.6 2.4	3.0	1.5	4.25 3.75	1.2 0.8	0.13



### Disclaimer

EVVOSEMI ("EVVO") reserves the right to make corrections, enhancements, improvements, and other changes to its products and services at any time, and to discontinue any product or service without notice.

EVVO warrants the performance of its hardware products to the specifications applicable at the time of sale in accordance with its standard warranty. Testing and other quality control techniques are used as deemed necessary by EVVO to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

Customers should obtain and confirm the latest product information and specifications before final design, purchase, or use. EVVO makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does EVVO assume any liability for application assistance or customer product design. EVVO does not warrant or accept any liability for products that are purchased or used for any unintended or unauthorized application.

EVVO products are not authorized for use as critical components in life support devices or systems without the express written approval of EVVOSEMI.

The EVVO logo and EVVOSEMI are trademarks of EVVOSEMI or its subsidiaries in relevant jurisdictions. EVVO reserves the right to make changes without further notice to any products herein.