

EVVOSEMI[®]

THINK CHANGE DO



ESD



TVS



MOS



LDO



Diode



Sensor



DC-DC

Product Specification

▶ Domestic	Part Number	DMG2305UX
▶ Overseas	Part Number	DMG2305UX
▶ Equivalent	Part Number	DMG2305UX

EV is the abbreviation of name EVVO

-20V P-Channel Enhancement Mode MOSFET

Description

The DMG2305UX uses advanced trench It utilizes the latest processing techniques to achieve the high cell density and reduces the on-resistance with high repetitive avalanche rating. These features combine to make this design an extremely efficient and reliable device for use in power switching application and a wide variety of other applications


Application

- Advanced MOSFET process technology
- Special designed for PWM, load switching and general purpose applications
- Ultra low on-resistance with low gate charge
- Fast switching and reverse body recovery
- 150°C operating temperature

General Features

- $V_{DS} = -20V, I_D = -4.2A$
- $R_{DS(ON)} = 33m\Omega @ V_{GS}=4.5V$
- $R_{DS(ON)} = 45m\Omega @ V_{GS}=2.5V$

SOT-23 Pin Configuration



Absolute max Rating: @T_A=25°C unless otherwise specified





Symbol	Parameter	Max.	Units
$I_D @ TC = 25^{\circ}C$	Continuous Drain Current, $V_{GS} @ 10V$	-4.2①	A
$I_D @ TC = 70^{\circ}C$	Continuous Drain Current, $V_{GS} @ 10V$	-2.4 ①	
I_{DM}	Pulsed Drain Current ②	-30	
$P_D @ TC = 25^{\circ}C$	Power Dissipation ③	1.4	W
V_{DS}	Drain-Source Voltage	-20	V
V_{GS}	Gate-to-Source Voltage	± 8	V
$T_J \ T_{STG}$	Operating Junction and Storage Temperature Range	-55 to +150	°C
$R_{\theta JA}$	Junction-to-ambient (t ≤ 10s) ④	90	°C /W

-20V P-Channel Enhancement Mode MOSFET
Electrical Characterizes @ $T_A=25^\circ\text{C}$ unless otherwise specified

Symbol	Parameter	Conditions	Min.	Typ.	Max.	Units
V(BR)DSS	Drain-to-Source breakdown voltage	$V_{GS} = 0V, I_D = -250\mu A$	-20	—	—	V
R _{DS(on)}	Static Drain-to-Source on-resistance	$V_{GS}=-4.5V, I_D = -4A$	—	33	35	mΩ
		$V_{GS}=-2.5V, I_D = -4A$	—	45	54	
		$V_{GS}=-1.8V, I_D = -2A$	—	60	70	
V _{GS(th)}	Gate threshold voltage	$V_{DS} = V_{GS}, I_D = -250\mu A$	-0.3	—	-1.0	V
		$T_J = 125^\circ\text{C}$	—	-0.44	—	
IDSS	Drain-to-Source leakage current	$V_{DS} = -16V, V_{GS} = 0V$	—	—	-1	μA
		$T_J = 125^\circ\text{C}$	—	—	-50	
IGSS	Gate-to-Source forward leakage	$V_{GS} = 8V$	—	—	10	μA
		$V_{GS} = -8V$	—	—	-10	
Q _g	Total gate charge	$I_D = -4A,$ $V_{DS}=-10V,$ $V_{GS} = -4.5V$	—	10	—	nC
Q _{gs}	Gate-to-Source charge		—	0.77	—	
Q _{gd}	Gate-to-Drain("Miller") charge		—	3.5	—	
t _{d(on)}	Turn-on delay time	$V_{GS}=-4.5V, V_{DS}=-10V,$ $R_{GEN}=3\Omega,$	—	10	—	ns
t _r	Rise time		—	8.6	—	
t _{d(off)}	Turn-Off delay time		—	29	—	
t _f	Fall time		—	13	—	
C _{iss}	Input capacitance	$V_{GS} = 0V, V_{DS}=-10V, f = 1\text{MHz}$	—	886.6	—	pF
C _{oss}	Output capacitance		—	140.6	—	
C _{rss}	Reverse transfer capacitance		—	129.2	—	

Notes:

- ① Calculated continuous current based on maximum allowable junction temperature.
- ② Repetitive rating; pulse width limited by max. junction temperature.
- ③ The power dissipation PD is based on max. junction temperature, using junction-to-case thermal resistance.
- ④ The value of $R_{\theta JA}$ is measured with the device mounted on 1 in 2 FR 4 board with 2oz. Copper, in a still air environment with $T_A = 25^\circ\text{C}$

-20V P-Channel Enhancement Mode MOSFET
Test circuits and Waveforms
EAS test circuit:

Gate charge test circuit:

Switching time test circuit:

Switch Waveforms:


-20V P-Channel Enhancement Mode MOSFET

Typical electrical and thermal characteristics




Figure 1: Typical Output Characteristics




Figure 2. Gate to source cut-off voltage




Figure 3. Drain-to-Source Breakdown Voltage Vs.

Case Temperature




Figure 4: Normalized On-Resistance Vs. Case

Temperature

-20V P-Channel Enhancement Mode MOSFET

Typical electrical and thermal characteristics




Figure 5. Maximum Drain Current Vs. Case Temperature




Figure 6. Typical Capacitance Vs. Drain-to-Source Voltage





Figure7. Maximum Effective Transient Thermal Impedance Junction-to-Case

-20V P-Channel Enhancement Mode MOSFET

Mechanical Data

SOT-23 PACKAGE OUTLINE DIMENSION



Symbol	Dimension In Millimeters		Dimension In Inches	
	Min	Max	Min	Max
A	0.900	1.150	0.035	0.045
A1	0.000	0.100	0.000	0.004
A2	0.900	1.050	0.035	0.041
b	0.300	0.500	0.012	0.020
c	0.080	0.150	0.003	0.006
D	2.800	3.000	0.110	0.118
E	1.200	1.400	0.047	0.055
E1	2.250	2.550	0.089	0.100
e	0.95TYP		0.037TYP	
e1	1.800	2.000	0.071	0.079
L	0.55REF		0.022REF	
L1	0.300	0.500	0.012	0.020
θ	0°	8°	0°	8°

Disclaimer

EVVOSEMI ("EVVO") reserves the right to make corrections, enhancements, improvements, and other changes to its products and services at any time, and to discontinue any product or service without notice.

EVVO warrants the performance of its hardware products to the specifications applicable at the time of sale in accordance with its standard warranty. Testing and other quality control techniques are used as deemed necessary by EVVO to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

Customers should obtain and confirm the latest product information and specifications before final design, purchase, or use. EVVO makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does EVVO assume any liability for application assistance or customer product design. EVVO does not warrant or accept any liability for products that are purchased or used for any unintended or unauthorized application.

EVVO products are not authorized for use as critical components in life support devices or systems without the express written approval of EVVOSEMI.

The EVVO logo and EVVOSEMI are trademarks of EVVOSEMI or its subsidiaries in relevant jurisdictions. EVVO reserves the right to make changes without further notice to any products herein.