

EVVOSEMI[®]

THINK CHANGE DO



ESD



TVS



MOS



LDO



Diode



Sensor



DC-DC

Product Specification

▶ Domestic	Part Number	LM317K
▶ Overseas	Part Number	LM317K
▶ Equivalent	Part Number	LM317K

EV is the abbreviation of name EVVO

◆ Features

- With TO-3 package
- 1, Adjust 2, Input 3, Output
- Output voltage range :1.2V to 37V
- Output current in excess of 1.5A



◆ Absolute maximum rating

Symbol	Parameter	Value	Unit
$V_i - V_o$	Input-output voltage differential	40	V
I_o	Output current	1.5	A
P_D	Power dissipation	Internally limited	W
T_{OP}	Operating junction temperature	0~+125	
T_{STG}	Storage temperature	-65~+125	

◆ Electrical characteristics

($V_i - V_o = 5V$, $I_o = 500mA$, $I_{MAX} = 1.5A$, $P_{MAX} = 20W$, unless otherwise specified)

Symbol	Parameter	Test conditions	Min	Typ.	Max	Unit
V_{REF}	Reference voltage	$V_i - V_o = 5V$ $I_o = 40mA$ to 500mA	1.2	1.25	1.3	V
V_o	Line regulation	$V_i - V_o = 3V$ to 40V $I_o = 500mA$			0.05	%/V
V_o	Load regulation	$V_i - V_o = 5V$ $I_o = 10mA$ to 1.5A			1.0	%
I_{ADJ}	Adjustment pin current	$V_i - V_o = 5V$ $I_o = 40mA$ to 500mA			100	μA
I_{ADJ}	Adjustment pin current	$V_i - V_o = 3V$ to 40V $I_o = 40mA$ to 500mA			5	μA
I_{ADJ}	Adjustment pin current	$V_i - V_o = 5V$ $I_o = 10mA$ to 1.5A			5	μA
S_{VR}	Ripple rejection	$V_o = 10V$; $I_o = 500mA$; $V_i - V_o = 5V$ $f = 100Hz$, $C_{ADJ} = 10 \mu F$	66			dB

Disclaimer

EVVOSEMI ("EVVO") reserves the right to make corrections, enhancements, improvements, and other changes to its products and services at any time, and to discontinue any product or service without notice.

EVVO warrants the performance of its hardware products to the specifications applicable at the time of sale in accordance with its standard warranty. Testing and other quality control techniques are used as deemed necessary by EVVO to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

Customers should obtain and confirm the latest product information and specifications before final design, purchase, or use. EVVO makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does EVVO assume any liability for application assistance or customer product design. EVVO does not warrant or accept any liability for products that are purchased or used for any unintended or unauthorized application.

EVVO products are not authorized for use as critical components in life support devices or systems without the express written approval of EVVOSEMI.

The EVVO logo and EVVOSEMI are trademarks of EVVOSEMI or its subsidiaries in relevant jurisdictions. EVVO reserves the right to make changes without further notice to any products herein.